
Paradox MG5000 MG5050





Security Alarms and Fire Systems - Control panels - Paradox MG5000 MG5050
Rating Not Rated Yet
Sales price £142.29
Discount
Tax amount

Ask a question about this product

Description

Paradox MG5000 MG5050

- **Features**
- StayD Mode
- Built-in transceiver (433 MHz or 868 MHz)
- 32 zones (any of which can be wireless)
- 32 users and 32 remote controls (one per user)
- 2 partitions
- 4-wire communication bus (connect up to 15 keypads)
- Supports RAC1, REM15, REM1, REM101, REM2, REM3 and REM25 remote controls
- Supports up to 8 K37 wireless keypads
- Supports up to 2 RPT1 wireless repeaters
- Supports PCS Series
- Supports IP150 Internet Module
- Supports VDMP3 Plug-in voice dialer
- Supports 16 PGMs (any of which can be wireless)
- App-based system control via Insite GOLD
- In-field firmware upgrade via 307USB and BabyWare
- Menu-driven programming for the Installer, Master and Maintenance codes
- Multiple telephone numbers for event reporting: 3 monitoring and 5 for Personal Dialing
- Patented 2 opto coupler dialer circuit - the most reliable dialer in the industry (US Patents 5751803, RE39406)
- Calendar with Daylight savings Time
- New Sleep arming method
- Push button power reset
- RF Jamming Supervision
- 9.6k baud communication with BabyWare
- 256 events buffered
- Supports Memory Key
- Fits in a 20 x 25.5 x 7.6 cm (8 x 10 x 3 in) metal box or in a
- 28 x 28 x 7.6 cm (11 x 11 x 3 in) metal box
- EN Certification now available for the MG5050 EN.
- Please note that Quick Menu Programming is not available in EN version 4.96
- MG5050 On-board PGMs 4
- MG5050 On-board Zones 5 (10w/ATZ)
- MG5000 On-board PGMs 2

- MG5000 On-board Zones 2 (4w/ATZ)

GBE Electronics LTD
Phone +44(0)2081237324 - Email gbeelectronics@gmail.com
Email web@gbeelectronics.com website gbeelectronics.com
Office Reg Address 128 City Road London EC1V 2NX United Kingdom